

FINITURA DEL DIFFUSORE



BC



CR/TR

FINITURA MONTATURA





NI

ELETTTRIFICAZIONI



► E27  2x77w 230V/50HZ E27

ALTERNATIVE:

 2x23w 230V/50HZ

 2x10w 230V/50HZ

ELETTTRIFICAZIONI LED

	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 3000K - 1850 LUMENS - NON DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 4000K - 1850 LUMENS - NON DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 3000K - 1850 LUMENS - NON DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 4000K - 1850 LUMENS - NON DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 3000K - 1850 LUMENS - DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 4000K - 1850 LUMENS - DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 3000K - 1850 LUMENS - DIMMERABILE
	1x20,5w 230V/50HZ	LED 20,5W - 33 VOLT (DRIVER INCLUSO) - 4000K - 1850 LUMENS - DIMMERABILE
	1x17,5w 230V/50HZ	LED 17,5W - 230 VOLT - 3000K - 1300 LUMENS - DIMMERABILE
	1x17,5w 230V/50HZ	LED 17,5W - 230 VOLT - 4000K - 1300 LUMENS - DIMMERABILE
	1x17,5w 230V/50HZ	LED 17,5W - 230 VOLT - 3000K - 1300 LUMENS - DIMMERABILE
	1x17,5w 230V/50HZ	LED 17,5W - 230 VOLT - 4000K - 1300 LUMENS - DIMMERABILE
	1x40w 230V/50HZ	LED 40W - 24 VOLT (DRIVER INCLUSO) - 3000K - 4050 LUMENS - NON DIMMERABILE
	1x40w 230V/50HZ	LED 40W - 24 VOLT (DRIVER INCLUSO) - 4000K - 4050 LUMENS - NON DIMMERABILE
	1x40w 230V/50HZ	LED 40W - 24 VOLT (DRIVER INCLUSO) - 3000K - 4050 LUMENS - NON DIMMERABILE
	1x40w 230V/50HZ	LED 40W - 24 VOLT (DRIVER INCLUSO) - 4000K - 4050 LUMENS - NON DIMMERABILE

MARCATURE:



VOLUME	Mc 0,07
PESO LORDO	Kg 8
PESO NETTO	Kg 5